

Updaters,

Pay serious heed to the following cautionary prerequisites and requirements:

1. **DISABLE MIDI CLOCK.** If you do not you will damage, possibly irreparably, your new Flash-ROM chip.
2. Set your MIDI interface to 1MHz (this has nothing to do with “tempo,” which is preset), or whatever your slowest transmission speed is; if you do not you will damage your Flash-ROM chip irreparably. If your interface doesn't allow you to define this value **DO NOT PROCEED.** Contact Analogia Inc. further instructions.
3. Save off your own sounds (i.e., ROM Banks A & B; RAM Banks C, D, and the MULTI Bank individually).
4. Follow these instructions to the letter—you are replacing your Omega’s operating system. **THIS IS SERIOUS BUSINESS.**
5. Load/Install omega2os171.mid. "Play it in" as you would any track sequence. You will be asked if you want to update O.S. Agree to proceed. Scramble Note: After O.S. is upgraded, MULTI patches from approximately 101–128 will be corrupted. Reload your saved MULTI bank.
6. Load Omega2Patches9–17–02.mid: consists of Bank A, Bank B and MULTI.
7. A successful update will return you to Patch Rom A 1.
8. To address possible knob adjustment anomalies, press the Oscillator edit switch, and reset master tune (reads TUNE) if necessary.

PLEASE NOTE: ANALOGIA INC. / STUDIO ELECTRONICS are not responsible for damage caused to your Flash-ROM chip by power surges, improperly grounded setups, or user error.

ANALOGIA INC.
530 West Palm Avenue
El Segundo CA 90245
Office: (310) 640–3546
Fax: (310) 640–3516
studioelectronics@sbcglobal.net
support@studioelectronics.com
facebook.com/pages/Studio-Electronics
twitter.com/SE_BoomStar
soundcloud.com/studio-electronics